

Instrument selector Switches 10Amp

Specifications : Rotary Switches conform to IS : 60947 (Part I and Part III)

Mechanism : Slow break principally for AC switching only.

Mounting : 6 Position - Universal, 8 Position - Back of Panel

Operating Handle : Knob (wing type) of black colour / red colour

Optional Accessories : A selection of accessories and attachments from a wide variety is available, viz Handle, Detachable Handles Indicating Plates - Details available on request.

Indicating Plates : The size of indicating plates for 6 position & 8 Position in 95mm X 95mm Rotary Selector Switches are suitable for instruments like ammeters, Voltmeters Power factor Meters etc. The design enables to indicate by means of a single meter, the currents or the voltages, Ammeter Selector Switches are provided with make before break contacts to give security against risk of open circuit of the current transformer secondaries. Listed below are standard switches.

TYPE : Open execution without any enclosure.

DESIGN : Air break wiping contacts (Double Break) silver plated, self aligning.

RATING : 10 amperes for working voltage of 250 or 440 for AC Circuits only.

MECHANISM : Slow break principally for AC switching only.

MOUNTING : For Switches flush at the back of panel mounting specify SRP for switches at the front of panel base mounting specify SBC

Operating Handle :

Knob (wing type) of black / red colour

SWITCHING		TYPE	DIM. Y	DIAGRAM
Current in each phase with OFF 4 positions 90° Indicating plate size 64 X 64 mm		SRP136MA60	40	
Current in each phase and leakage or out of balance current with OFF 6 positions 60 Indicating plate size 88 X 88 mm		SRP1148MF42/S	52	
Current in each phase and neutral and leakage current with OFF 6 positions 60 Indicating plate size 88 X 88 mm		SRP1210MA43/S	64	

VOLTMETER SELECTOR

Voltage between phase and neutral with OFF 4 position 90° Indicating plate size 64 X 64 mm		SRP135VS	34	
Voltage between phase and neutral with OFF 4 position 90° Indicating plate size 64 X 64 mm		SRP115BE18	34	
Voltage between phases and between phase and neutral without OFF 6 positions 60 Indicating plate size 88 X 88 mm		SRP137SV	46	

SPECIAL SELECTOR SWITCHES

With one switch to indicate, with one Ammeter & one Voltmeter. Simultaneous reading of phase current & Voltage between phases with an OFF position. Indicating plate size 64 X 64 mm		SRP1310MB28	64	
4 Pos. Ammeter selector switch Direct in line without 'CT's Indicating plate size 64 X 64 mm		SRP1313ZZF12	82	

- Add GB in code for switches required with Grey F.P. and Black Knob. Alternatively add YR for Yellow F.P. and Red Knob. If either codes are not specified, then we shall book order with GB.